



## SPECIFICATIONS

FREQUENCY RANGE: DC TO 26.5 GHz

IMPEDANCE: 50 OHMS

INSERTION LOSS: 8.5 dB

INPUT POWER: 1 WATT AVERAGE

AMPLITUDE TRACKING: 1 dB

TEMPERATURE RANGE: -65°C TO +125°C

PHASE TRACKING:  $\pm 4^\circ$

MAXIMUM INPUT VSWR: 1.40:1

\*OUTPUT PORTS ARE SYMMETRICAL TO MALE INPUT\*

\*2.9mm CONNECTORS WILL MATE WITH SMA, 3.5mm AND K CONNECTORS. THE K CONNECTOR IS A TRADEMARK OF ANRITSU CORPORATION\*



**PASTERNAK ENTERPRISES, INC.**

P.O BOX 16759, IRVINE, CA 92623  
PHONE (949) 261-1920 FAX (949) 261-7451

WEB ADDRESS: [www.pasternack.com](http://www.pasternack.com)  
E-MAIL ADDRESS: [sales@pasternack.com](mailto:sales@pasternack.com)

**COAXIAL & FIBER OPTICS**

DWG TITLE

**PE2065**

DES.

2.9mm FEMALE-MALE-FEMALE, RESISTIVE  
POWER DIVIDER, FREQUENCY RANGE: DC  
TO 26.5 GHz

REV. A

**FSCM NO. 53919**

CAD FILE

110211

SCALE N/A

SIZE A

2233

NOTES:

1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.
3. DIMENSIONS ARE IN INCHES [mm].